

# Infrared detector modules with preamps



Metal dewar type

## High sensitivity modules of easy-to-use

These devices combine a dewar type detector with a compatible preamplifier, and easily operate to detect infrared radiation just by connecting to a DC power supply. InGaAs and InSb detectors are provided as standard devices (liquid nitrogen cooling). Custom-designed devices with different active areas, FOV or amplifier gain, etc. are also available to meet your specific needs.

### Features

- ➔ **Compact integral detector unit**
- ➔ **Optimum connections between the detector element and pre-amplifier allow amplified signals to be easily obtained.**

#### Required power supply specifications

- G7754 series, P7751 series:  $\pm 15$  V ( $\pm 12.0$  to  $\pm 17.5$  V can also be used)
- Current capacity: 1.5 times or more of each module's maximum current consumption
- Ripple noise: 5 mVp-p or less
- Analog power supply only
- Recommended DC power supplies: PW18-3AD (TEXIO)  
E3620A, E3630A (Keysight Technologies)

### Applications

- ➔ **Infrared detection**

### Accessories

- ➔ **Cable (for DC power supply):**  
2 m (connector installed at one end) **A4372-02**
- ➔ **BNC-BNC coaxial cable (for signal output): 2 m**
- ➔ **Instruction manual**

### Specifications / Absolute maximum ratings

Type No.	Detector element	Active area (mm)	External power supply*1				Absolute maximum ratings		
			Supply voltage (V)			Supply capacitance (mA)	External input voltage (V)	Operating temperature Topr (°C)	Storage temperature Tstg (°C)
			Min.	Typ.	Max.				
G7754-01	InGaAs (G12183-010 chip)	$\phi 1$	$\pm 12.0$	$\pm 15.0$	$\pm 17.5$	$\pm 23$	$\pm 18$	0 to +40	-20 to +50
G7754-03	InGaAs (G12183-030 chip)	$\phi 3$							
P7751-01	InSb (P5968-060)	$\phi 0.6$				$\pm 30$			
P7751-02	InSb (P5968-200)	$\phi 2$							

\*1: Use only an analog power supply.

Note: Nitrogen hold time: 12 hours or more (at the time of shipment)

Exceeding the absolute maximum ratings even momentarily may cause a drop in product quality. Always be sure to use the product within the absolute maximum ratings.

### Electrical and optical characteristics (Typ.)


Type No.	Measurement condition	Peak sensitivity wavelength $\lambda_p$ ( $\mu\text{m}$ )	Cut-off wavelength $\lambda_c$ ( $\mu\text{m}$ )	Photo sensitivity S $\lambda = \lambda_p$ (V/W)	Noise equivalent power NEP $\lambda = \lambda_p$ (W/Hz <sup>1/2</sup> )	Cutoff frequency $f_c$ (Hz)	Output impedance ( $\Omega$ )	Maximum output voltage RL=1 k $\Omega$ (V)	Maximum current consumption*3 (mA)
	Element temperature T (°C)								
G7754-01	-196	2.0	2.4	$2 \times 10^9$	$3 \times 10^{-14}$	2 to 500	50	$\pm 10$	$\pm 15$
G7754-03				$5 \times 10^8$	$1.5 \times 10^{-13}$	2 to 500		$\pm 10$	$\pm 15$
P7751-01*4		5.3	5.5	$3 \times 10^8$	$3 \times 10^{-13}$	5 to 10000		$\pm 10$	$\pm 20$
P7751-02*4				$1.5 \times 10^8$	$1 \times 10^{-12}$	5 to 12000		$\pm 10$	$\pm 20$

\*2:  $f=100$  Hz (G7754-01, G7754-03),  $f=1.2$  kHz (P7751-01, P7751-02)

\*3:  $V_s = \pm 15$  V


\*4: FOV=60°

**Spectral response**





KIRD80076EG

**Dimensional outline (unit: mm)**



KIRDA0010EE

Cable (for DC power supply) A4372-02



Pin no.	Pin connection	Lead color
①	-Vs	Blue
②	GND	Black/white/blue stranded wire
③	GND	
④	+Vs	White

KIRDA0196EB

**Precaution for use**

- The detector should not be placed horizontally during use.
- Using these detectors in an environment subjected to vibration may cause microphonic noise. Take measures to prevent vibration as needed.

**Related information**

[www.hamamatsu.com/sp/ssd/doc\\_en.html](http://www.hamamatsu.com/sp/ssd/doc_en.html)

■ Precautions

- Notice

■ Technical information

- Infrared detector

Information described in this material is current as of April, 2019.

Product specifications are subject to change without prior notice due to improvements or other reasons. This document has been carefully prepared and the information contained is believed to be accurate. In rare cases, however, there may be inaccuracies such as text errors. Before using these products, always contact us for the delivery specification sheet to check the latest specifications.

The product warranty is valid for one year after delivery and is limited to product repair or replacement for defects discovered and reported to us within that one year period. However, even if within the warranty period we accept absolutely no liability for any loss caused by natural disasters or improper product use. Copying or reprinting the contents described in this material in whole or in part is prohibited without our prior permission.

**HAMAMATSU**

[www.hamamatsu.com](http://www.hamamatsu.com)

HAMAMATSU PHOTONICS K.K., Solid State Division

1126-1 Ichino-cho, Higashi-ku, Hamamatsu City, 435-8558 Japan, Telephone: (81)53-434-3311, Fax: (81)53-434-5184

U.S.A.: Hamamatsu Corporation, 360 Foothill Road, Bridgewater, N.J. 08807, U.S.A., Telephone: (1)908-231-0960, Fax: (1)908-231-1218, E-mail: [usa@hamamatsu.com](mailto:usa@hamamatsu.com)  
 Germany: Hamamatsu Photonics Deutschland GmbH: Arzbergerstr. 10, D-82211 Herrsching am Ammersee, Germany, Telephone: (49)8152-375-0, Fax: (49)8152-265-8, E-mail: [info@hamamatsu.de](mailto:info@hamamatsu.de)  
 France: Hamamatsu Photonics France S.A.R.L.: 19, Rue du Saule Trapu, Parc du Moulin de Massy, 91882 Massy Cedex, France, Telephone: (33)1 69 53 71 00, Fax: (33)1 69 53 71 10, E-mail: [infos@hamamatsu.fr](mailto:infos@hamamatsu.fr)  
 United Kingdom: Hamamatsu Photonics UK Limited, 2 Howard Court, 10 Tewin Road, Welwyn Garden City, Hertfordshire AL7 1BW, United Kingdom, Telephone: (44)1707-294888, Fax: (44)1707-325777, E-mail: [info@hamamatsu.co.uk](mailto:info@hamamatsu.co.uk)  
 North Europe: Hamamatsu Photonics Norden AB: Torshamnsgatan 35 16440 Kista, Sweden, Telephone: (46)8-509 031 00, Fax: (46)8-509 031 01, E-mail: [info@hamamatsu.se](mailto:info@hamamatsu.se)  
 Italy: Hamamatsu Photonics Italia S.r.l.: Strada della Moia, 1 int. 6, 20020 Arese (Milano), Italy, Telephone: (39)02-93 58 17 33, Fax: (39)02-93 58 17 41, E-mail: [info@hamamatsu.it](mailto:info@hamamatsu.it)  
 China: Hamamatsu Photonics (China) Co., Ltd.: B1201, Jiaming Center, No.27 Dongsanhuan Beilu, Chaoyang District, 100020 Beijing, P.R.China, Telephone: (86)10-6586-6006, Fax: (86)10-6586-2866, E-mail: [hpc@hamamatsu.com.cn](mailto:hpc@hamamatsu.com.cn)  
 Taiwan: Hamamatsu Photonics Taiwan Co., Ltd.: 8F-3, No. 158, Section2, Gongdao 5th Road, East District, Hsinchu, 300, Taiwan R.O.C. Telephone: (886)3-659-0080, Fax: (886)3-659-0081, E-mail: [info@hamamatsu.com.tw](mailto:info@hamamatsu.com.tw)