

D-TYPE ACTIVE MODULE E5771-01 for 28 mm Side-on PMT

The E5771-01 is a voltage divider to operate a 28 mm Side-on photomultiplier tube. The compact configuration is convenient to attach directly on tracing circuit board. Additionally, the built-in circuit utilizes transistor devices in the final three stages, so that the E5771-01 can give superior DC linearity characteristic under a low power consumption.



SPECIFICATIONS

Parameter	Description / Value	Unit
Applicable PMT	28 mm Side-on type	
Max. Supply Voltage between Case and Pins	1500	V
Max. Supply Voltage between Pin#1 and #11	1500	V
Max. Divider Current between Pin#1 and #11	0.29	mA
Max. Power Consumption Between Pin#1 and #11	0.44 (at 1500 V)	W
Insulation Resistance between Case and Pins Min.	1 × 10 ¹¹	Ω
Voltage Distribution Ratio among Pin#1 to #11	1: 1: 1: : 1: 1: 1	_
Max. Linear Output in DC Mode Typ.	100	μΑ
Operating Temperature	-20 to +50	°C

Figure 1: DC Linearity of E5771-01





Figure 2: Maximum Output under ±1 % DC Linearity of E5771-01



Subject to local technical requirements and regulations, availability of products included in this promotional material may vary. Please consult with our sales office. Information furnished by HAMAMATSU is believed to be reliable. However, no responsibility is assumed for possible inaccuracies or omissions. Specifications are subject to change without notice. No patent rights are granted to any of the circuits described herein. ©2011 Hamamatsu Photonics K.K.

D-TYPE ACTIVE MODULE E5771-01

Figure 3: Dimensional Outline and Circuit Diagram of E5771-01 (Unit: mm)






Figure 4: The Example of Completed Divider Circuit with E5771-01



TACCA0180EC TAC

Figure 5: The Example of How to Use



CAUTION

- When getting output anode current over operating area shown at Figure 2, there may be a sudden change in output. It would be caused by divider current but not lead E5771-01 to break down.
- When supplying high voltage with opposite polarity by mis-handling in connection with E5771-01 mounted on a printed circuit board, it might lead an internal damage in E5771-01.
- Therefore, please take care to see the polarity of high voltage and correct electro-connections before operation.
- Also, if short-circuit should be produced by mistake or something among pin#1 to #11 in operation, it may lead an internal Damage in E5771-01.
- The specifications described herein are subject to change without notice.

HAMAMATSU PHOTONICS K.K. www.hamamatsu.com

HAMAMATSU PHOTONICS K.K., Electron Tube Division

314-5, Shimokanzo, Iwata City, Shizuoka Pref., 438-0193, Japan, Telephone: (81)539/62-5248, Fax: (81)539/62-2205

U.S.A.: Hamamatsu Corporation: 360 Foothill Road, P. O. Box 6910, Bridgewater, N.J. 08807-0910, U.S.A., Telephone: (1)908-231-10960, Fax: (1)908-231-1218 E-mail: usa@hamamatsu.com

Germany: Hamamatsu Photonics Deutschland GmbH: Arzbergerstr. 10, D-82211 Herrsching am Ammersee, Germany, Telephone: (49)8152-375-0, Fax: (49)8152-2658 E-mail: info@hamamatsu.de

France: Hamamatsu Photonics France S.A.R.L.: 19, Rue du Saule Trapu, Parc du Moulin de Massy, 91882 Massy Cedex, France, Telephone: (33) 1 69 53 71 10, Fax: (33) 1 69 53 71 10 E-mail: info@hamamatsu.fr

United Kingdom: Hamamatsu Photonics UK Limited: 2 Howard Court, 10 Tewin Road Welwyn Gedre City Hertfordshire AL7 1BW, United Kingdom, Telephone: 44-(0)1707-29488, Fax: 44(0)1707-325777 E-mail: info@hamamatsu.co.uk

North Europe: Hamamatsu Photonics Norden AB: Smidesvägen 12, SE-171-41 SOLNA, Sweden, Telephone: (46)8-509-031-00, Fax: (46)8-509-031-01 E-mail: info@hamamatsu.se

TACC1050E01

OCT. 2011. IP